



DC analogue voltmeters

Indicators and transducers

Indicators and transducers



voltm_015.eps

Compliance with standards

- > IEC 60051-1
- > IEC 60414
- > NF EN 60051-1
- > DIN 43780
- > NF C 42-010
- > VDE 0410
- > BS 5448
- > BS 89



Function

SOCOME **magnetic-electric voltmeters** measure the DC voltage on any electrical circuit.

They are embedded in the front panel of cabinets, enclosures or other equipment.

Characteristics


- Pointer deflection: 90°.
- Insulating voltage: 660 V.
- Dielectric quality: 2 kV - 50 Hz - 1 mn.
- Consumption: internal resistance 1000 Ω/V.
- Any voltage above 600 V requires a voltage divider.
- Connection: screw or fast-on lugs.
- Interchangeable guided dial (needle protection).

Composition of the range

| Case | DIN 48-72-96 | ROTEX 72 |
|--------------------|--------------|----------|
| Pointer deflection | 90° | 90° |
| Rating | | |
| 0 - 25 - 250 V | • | • |
| 0 - 400 - 500 V | • | • |


Case

DIN




| Pointer deflection: 90° | | | | |
|-------------------------|-------------|--------------------|----|-----|
| A | B | C | D | E |
| 48 x 48 | 44.5 x 44.5 | 45 ^{+0.6} | 59 | 38 |
| 72 x 72 | 66.5 x 66.5 | 68 ^{-0.7} | 58 | 65 |
| 96 x 96 | 89 x 89 | 92 ^{-0.8} | 58 | 100 |

ROTEX



| Pointer deflection: 90° | | | | | | |
|-------------------------|------|----|------|--------------------|------|------|
| A | B | C | D | E | F | G |
| 72 x 72 | 54.5 | 11 | 28.5 | 56 ^{±0.5} | 34.5 | 50.8 |

Connections



References

| Rating | Direct connection | | | |
|-----------|------------------------|------------------------|------------------------|-------------------------|
| | DIN 48x48 D48C90-V | DIN 72x72 D72C90-V | DIN 96x96 D96C90-V | ROTEX 72x72 R72C90-V |
| 0 - 25 V | Reference 192G 5012 | Reference 192G 5112 | Reference | Reference 192G 6112 |
| 0 - 40 V | Reference 192G 5013 | Reference 192G 5113 | Reference 192G 5213 | Reference 192G 6113 |
| 0 - 60 V | Reference 192G 5014 | Reference 192G 5114 | Reference 192G 5214 | Reference 192G 6114 |
| 0 - 100 V | Reference 192G 5015 | Reference | Reference 192G 5215 | Reference 192G 6115 |
| 0 - 150 V | Reference 192G 5016 | Reference 192G 5116 | Reference 192G 5216 | Reference 192G 6116 |
| 0 - 250 V | | Reference 192G 5117 | | |
| 0 - 400 V | | | | Reference 192G 6119 |
| 0 - 500 V | | Reference 192G 5120 | Reference 192G 5220 | |

Accessories

| | DIN 48x48 D48A90-A | DIN 72x72 D72A90-A | DIN 96x96 D96A90-A | ROTEX 72x72 R72A90-A |
|-----------------------------|-----------------------|-----------------------|-----------------------|-------------------------|
| | Reference | Reference | Reference | Reference |
| Terminal protection cover | | 192Z 1000 | 192Z 1011 | |
| 2 safety caps | 192Z 1016 | 192Z 1016 | 192Z 1016 | 192Z 1016 |
| Mounting bracket and screws | 179Z 5000 | 179Z 5010 | 179Z 5010 | 179Z 5020 |
| Gasket | 192Z 0007 | 192Z 0008 | 192Z 0009 | 192Z 0011 |
| Replacement glass | 179Z 2000 | 179Z 2010 | 179Z 2020 | 179Z 2030 |